

XCAM1080P Series Camera Help Manual



Contents

Contents	I
1 The Application of the XCAM1080P Series Camera	1
2 XCAM1080P Series Camera's Datasheet(3)	1
3 Dimension of XCAM1080P Series Camera	3
4 XCAM1080P Series Camera Packing Information(TBD)	4
5 Software and App	4
6 XCAM1080P Series Camera Application Configurations	5
6.1 Camera Working Standalone with Built-in XCamView Software	5
6.2 Connecting camera to the PC with USB Video port	5
7 Brief Introduction of XCAM1080P Series Camera's UI and Its Functions.....	6
7.1 XCamView UI	6
7.2 The Camera Control Panel on the Left Side of the Video Window	7
7.3 The Measurement Toolbar on Top of the Video Window	7
7.4 Icons and Functions of the Synthesis Camera Control Toolbar at the Bottom of the Video Window.....	9
8 Sample Photos Captured with XCAM1080P Series Camera.....	15
9 Contacting Customer Service	15

1 The Application of the XCAM1080P Series Camera



Figure 1-1 The XCAM1080P Camera

The XCAM1080P series camera is intended to be used for the acquisition of digital images from the stereo microscope and biological microscope. The basic characteristic is listed as below:

- Sony Exmor back illuminated CMOS sensor
- 1080P HDMI/USB multiple video outputs
- SD card for the captured image and video storage
- Embedded XCamView for the control of the camera
- With strong ISP and other related processing functions
- ToupView/ToupLite software for PC
- ToupLite software for MAC

2 XCAM1080P Series Camera's Datasheet(3)

Order Code	Sensor & Size(mm)	Pixel(μm)	G Sensitivity Dark Signal	FPS/Resolution	Binning	Exposure(ms)
XCAM1080P2MPA	Sony IMX385(C) 1/2"(7.2x4.05)	3.75x3.75	1175mv with 1/30s 0.15mv with 1/30s	60@1920*1080(HDMI) 50@1920*1080(USB)	1x1	0.04~1000
XCAM1080P8MPA (discontinued)	Sony IMX334(C) 1/1.8"(7.68x4.32)	2.0x2.0	505mv with 1/30s 0.1mv with 1/30s	60@1920*1080(HDMI) 30@3840*2160(USB)	1x1	0.04~1000
XCAM1080P8MPB	Sony IMX415(C) 1/2.8"(5.57x3.13)	1.45x1.45	300mv with 1/30s 0.13mv with 1/30s	30@1920*1080(HDMI) 30@3840*2160(USB)	1x1	0.04~1000



Figure 2-1 Available Ports on the Back Panel of the Camera Body

The XCAM1080P Series Camera Help Manual

Interface	Function Description
USB Mouse	Connect USB mouse for easy operation with embedded XCamView software;
USB Video	Connect PC or other host device to realize video image transmission;
HDMI	Comply with HDMI1.4 standard. 1080P format video output for standard monitor;
DC12V	Power adapter connection (12V/1A);
SD	Comply with SDIO3.0 standard and SD card could be inserted for video and images storage;
LED	LED status indicator;
ON/OFF	Power switch;
Video Output Interface	Function Description
HDMI Interface	Comply with HDMI1.4 standard; 60fps@1080P;
USB Video Interface	Connecting USB port of PC for video transfer; MJPEG format video;
Function Name	Function Description
Video Saving	Video format: 1920*1080 H264/H265 encoded MP4 file; Video saving frame rate: 60fps(XCAM1080P2MPA);30fps(XCAM1080P8MPB)
Image Capture	2M (1920*2160, XCAM1080P2MPA) JPEG/TIFF image in SD card; 8M (3840*2160, XCAM1080P8MPB) JPEG/TIFF image in SD card;
Measurement Saving	Measurement information saved in layer mode with image content; Measurement information is saved together with image content in burn in mode.
ISP Function	Exposure(Automatic / Manual Exposure) / Gain, White Balance(Manual / Automatic / ROI Mode), Sharpening, 3D Denoise, Saturation Adjustment, Contrast Adjustment, Brightness Adjustment, Gamma Adjustment, Color to Gray, 50HZ/60HZ Anti-flicker Function
Image Operations	Zoom In/Zoom Out, Mirror/Flip, Freeze, Cross Line, Overlay, Embedded Files Browser, Video Playback, Measurement Function
Embedded RTC(Optional)	To support accurate time on board
Restore Factory Settings	Restore camera parameters to its factory status
Multiple Language Support	English / Simplified Chinese / Traditional Chinese / Korean / Thai / French / German / Japanese / Italian / Russian
Software Environment under USB Video Output	
White Balance	Auto White Balance
Color Technique	Ultra-Fine Color Engine
Capture/Control SDK	Windows/Linux/macOS/Android Multiple Platform SDK(Native C/C++, C#/VB.NET, Python, Java, DirectShow, Twain, etc)
Recording System	Still Picture or Movie
Operating System	Microsoft® Windows® XP / Vista / 7 / 8 / 8.1 /10(32 & 64 bit) OSx(Mac OS X) Linux
PC Requirements	CPU: Equal to Intel Core2 2.8GHz or Higher
	Memory: 4GB or More
	Ethernet Port: RJ45 Ethernet Port
	Display:19" or Larger
	CD-ROM
Operating Environment	
Operating Temperature (in Centidegree)	-10°~ 50°
Storage Temperature (in Centidegree)	-20°~ 60°
Operating Humidity	30~80%RH
Storage Humidity	10~60%RH

3 Dimension of XCAM1080P Series Camera



Figure 3-1 Dimension of XCAM1080P Series

4 XCAM1080P Series Camera Packing Information(TBD)



Figure 4-1 The XCAM1080P Series Camera Packing Information

Standard Packing List		
A	Gift box: L:25.5cm W:17.0cm H:9.0cm (1pcs,1.47kg/ box)	
B	One XCAM1080P series camera	
C	Power Adapter: Input: AC 100~240V 50Hz/60Hz, Output: DC 12V 1A European standard: Model:GS12E12-P11 12W/12V/1A; TUV(GS)/CB/CE/ROHS American standard: Model: GS12U12-P11 12W/12V/1A: UL/CUL/BSMI/CB/FCC EMI Standard:EN55022,EN61204-3, EN61000-3-2,-3, FCC Part 152 class B, BSMI CNS14338 EMS Standard:EN61000-4-2,3,4,5,6,8,11,EN61204-3,Class A Light Industry Standard	
D	USB Mouse	
E	HDMI cable	
F	USB2.0 A male to A male gold-plated connectors cable /2.0m	
G	CD (Driver & utilities software, Ø12cm)	
Optional Accessory		
H	SD card(16G or above; Speed: class 10)	
I	Adjustable lens adapter	C-Mount to Dia.23.2mm eyepiece tube (Please choose 1 of them for your microscope) 108001/AMA037 108002/AMA050 108003/AMA075
J	Fixed lens adapter	C-Mount to Dia.23.2mm eyepiece tube (Please choose 1 of them for your microscope) 108005/FMA037 108006/FMA050 108007/FMA075 Note: For K and L optional items, please specify your camera type(C-mount, microscope camera or telescope camera), ToupTek engineer will help you to determine the right microscope or telescope camera adapter for your application;
K	108015(Dia.23.2mm to 30.0mm Ring)/Adapter rings for 30mm eyepiece tube	
L	108016(Dia.23.2mm to 30.5mm Ring)/ Adapter rings for 30.5mm eyepiece tube	
M	Calibration kit	106011/TS-M1(X=0.01mm/100Div.); 106012/TS-M2(X,Y=0.01mm/100Div.); 106013/TS-M7(X=0.01mm/100Div., 0.10mm/100Div.)

5 Software and App

The software or the APP can be downloaded from the following link:

Windows: <http://www.touptek.com/download/showdownload.php?lang=en&id=33>

Linux & macOS: <http://www.touptek.com/download/showdownload.php?lang=en&id=28>

6 XCAM1080P Series Camera Application Configurations

You can use the XCAM1080P series camera in two different ways. Each application requires different hardware environment.

6.1 Camera Working Standalone with Built-in XCamView Software



Figure 6-1 XCAM1080P Series Camera with the HDMI Displayer

For this application, apart from the microscope, the user only needs an [XCAM1080P](#) series camera, an HDMI displayer, an HDMI cable, an SD card, a USB mouse and a power adapter that come with the camera. The steps to start the camera are listed as below:

- Connect the camera to a HDMI displayer using the HDMI cable;
- Insert the supplied USB mouse to the camera's USB port;
- Insert the supplied SD card into the [XCAM1080P](#) series camera SD card slot;
- Connect power adapter to the camera and switch it on;
- Switch on the displayer and view the video in the [XCamView](#) software. Move the mouse to the left, top or bottom of the [XCamView](#) UI, different control panel or UI will pop up and users could operate with the mouse at ease.

6.2 Connecting camera to the PC with USB Video port

For Windows user (Windows XP (32bit), Windows 7/8/10 (32/64 bit)), please use [ToupView](#).

For macOS and Linux user (macOS 10.10 or above or Linux distributions with kernel 2.6.27 or higher), please use [ToupLite](#).

The steps to start the camera are listed below:

- Install the [ToupView/ToupLite](#) on your PC;
- Connect power adapter to the camera and switch it on. After starting the camera, plug one end of the USB cable into the USB 2.0 Video port of the [XCAM1080P](#) series camera, and plug the other end into the USB port of the PC;
- Open [ToupView/ToupLite](#) software. The [XCAM1080P](#) series camera will be recognized automatically by software. In [ToupView/ToupLite](#) software, select the corresponding [XCAM1080P](#) series camera by clicking the camera name in the camera list.

Note:

When the USB cable and the mouse are plugged into the camera at the same time, the USB cable is preferred and the mouse is not available; when the USB cable is unplugged, the mouse can be used normally.

7 Brief Introduction of XCAM1080P Series Camera's UI and Its Functions

7.1 XCamView UI










Figure 7-1 The XCAM1080P Series Camera Control GUI

Notes	
1	To show the Camera Control Panel , move your mouse to the left of the video window. See Sec.7.2 for details.
2	Move the mouse cursor to the top of the video window, a Measurement Toolbar will pop up for calibration and measurement operations. When user left-clicks the Float/Fixed button  on the Measurement Toolbar , the Measurement Toolbar will be fixed. In this case the Camera Control Panel will not pop up automatically even if users move mouse cursor to left side of the video window. Only when user left-clicks the  button on the Measurement Toolbar to exit from measuring operations will they be able to do other operations on the Camera Control Panel , or the Synthesis Camera Control Toolbar . During the measuring operations, when a specific measuring object is selected, an Object Location & Attributes Control Bar  will appear for changing location and properties of the selected object. See Sec.7.4 for details.
3	When users move mouse cursor to the bottom of the video window, the Synthesis Camera Control Toolbar will pop up automatically.  . See Sec.7.4 for details.





7.2 The Camera Control Panel on the Left Side of the Video Window

The **Camera Control Panel** controls the camera to achieve the best video or image quality according to the specific applications; It will pop up automatically when the mouse cursor is moved to the left side of the video window (in measurement status, the **Camera Control Panel** will not pop up. The **Camera Control Panel** will only pop up when the measurement operations are finished or terminated while user's cursor on the left edge of the video window). Left-clicking  button to achieve **Display/Auto Hide** switch of the **Camera Control Panel**.

Camera Control Panel	Function	Function Description
	Snap	Capture image and save it to the SD card
	Record	Record video and save it to the SD card
	Auto Exposure	When Auto Exposure is checked, the system will automatically adjust Exposure Time and Gain according to the value of exposure compensation
	Exposure Compensation	Available when Auto Exposure is checked. Slide to left or right to adjust Exposure Compensation according to the current video brightness to achieve proper brightness value
	Exposure Time	Available when Auto Exposure is not checked. Slide to left or right to reduce or increase Exposure Time , adjusting brightness of the video
	Gain	Adjust Gain to reduce or increase brightness of video. The Noise will be reduced or increased accordingly
	Auto White Balance	White Balance adjustment according to the video continuously
	Manual White Balance	Adjust the Red or Blue slide bar to set the video White Balance .
	ROI White Balance	White Balance could be adjusted when the ROI region is changed according to content inside the ROI region.
	Red	Slide to left or right to decrease or increase the proportion of Red item in RGB on video
	Green	Slide to left or right to decrease or increase the proportion of Green item in RGB on video
	Blue	Slide to left or right to decrease or increase the proportion of Blue item in RGB on the video
	Sharpness	Adjust Sharpness level of the video
	Denoise	Slide left or right to Denoise the video
	Saturation	Adjust Saturation level of the video
	Gamma	Adjust Gamma level of the video. Slide to the right side to increase Gamma and to the left to decrease Gamma .
	Contrast	Adjust Contrast level of the video. Slide to the right side to increase Contrast and to the left to decrease Contrast .
	Brightness	Adjust Brightness level of the video. Slide to the right side to increase Brightness and to the left to decrease Brightness .
	DC	For DC illumination, there will be no fluctuation in light source so no need for compensating light flickering
	AC(50HZ)	Check AC(50HZ) to eliminate flickering caused by 50Hz light source
AC(60HZ)	Check AC(60HZ) to eliminate flickering caused by 60Hz light source	
Default	Restore all the settings in the Camera Control Panel to default values	

7.3 The Measurement Toolbar on Top of the Video Window



The **Measurement Toolbar** will pop up when moving mouse cursor to any place near the upper edge of the video window. Here is the introduction of the various functions on the **Measurement Toolbar**:


Icon	Function
	Float/ Fix switch of the Measurement Toolbar
<input checked="" type="checkbox"/> Visible	Show / Hide Measurement Objects
Nanometer (nm)	Select the desired Measurement Unit
4X	Select Magnification for measurement after Calibration
	Object Select
	Angle
	4 Points Angle

The XCAM1080P Series Camera Help Manual

	Point
	Arbitrary Line
	3 Points Line
	Horizontal Line
	Vertical Line
	3 Points Vertical Line
	Parallel
	Rectangle
	Ellipse
	5 Points Ellipse
	Circle
	3 Points Circle
	Annulus
	Two Circles and its Center Distance
	3 Points Two Circles and its Center Distance
	Arc
	Text
	Polygon
	Curve
	Scale Bar
	Arrow
	Execute Calibration to determine the corresponding relation between magnification and resolution, which will establish the corresponding relationship between Measurement Unit and the sensor pixel size. Calibration needs to be done with the help of a micrometer. For detailed steps of carrying out Calibration , please refer to ToupView help manual.
	Export the Measurement information to CSV file(*.csv)
	Measurement Setup
	Delete all the measurement objects from
	Exit from Measurement mode
	When the measurement ends, left-click on a single measuring object and the Object Location & Properties Control Bar will show up. User could move the object by dragging the object with the mouse. But more accurate movement could be done with the control bar. The icons on the control bar mean Move Left , Move Right , Move Up , Move Down , Color Adjustment and Delete .













Note:


1) When user left-clicks [Display/Hide](#) button  on the [Measurement Toolbar](#), the [Measurement Toolbar](#) will be fixed. In this case the [Camera Control Panel](#) will not pop up automatically even if moving the mouse cursor to the left edge of the video window. Only when user left-click the  button on the [Measurement Toolbar](#) to exit from the measurement mode will they be able to doing other operations with the [Camera Control Panel](#) or the [Synthesis Camera Control Toolbar](#).

2) When a specific **Measurement Object** is selected during the measurement operation, the **Object Location & Attributes Control Bar**  will appear for changing the object location and properties of the selected objects.

7.4 Icons and Functions of the Synthesis Camera Control Toolbar at the Bottom of the Video Window



Icon	Function	Icon	Function
	Zoom In the video Window		Zoom Out the video Window
	Horizontal Flip		Vertical Flip
	Color/Gray		Video Freeze
	Display Cross Line		Overlay
	Compare Image with the current video		Browse Images and Videos in the SD Card
	Settings		Check the Version of XCamView

The  **Setting** function is relatively more complicated than the other functions. Here are more details about it:

7.4.1 Setting>Measurement





Figure 7-2 The Measurement Setup

Global	Precision	Used to set the number of digits after the decimal point of the measurement result
Calibration	Line Width	Used for defining width of the lines for Calibration;
	Color	Used for defining color of the lines for Calibration;
	EndPoint	Type: Used for defining shape of the Endpoint of lines for calibration: Null means no EndPoint, rectangle means rectangle type of Endpoint. It makes alignment more easily;
Point, Angle, Line, Horizontal Line, Vertical Line, Rectangle, Circle, Ellipse, Annulus, Two Circles, Polygon, Curve		
Left-click the  along with the Measurement command mentioned above will unfold the corresponding attribute settings to set the individual property of the Measurement Objects.		

7.4.2 Setting>Magnification




Figure 7-3 Comprehensive Magnification Calibration Settings Page

Name	The name of the Magnification , usually the Magnification of the objective of the microscope is used as the Magnification name when calibration, such as 4X , 10X , 40X , 100X , etc. Besides, other user-defined information could be added into the Magnification name too, for example, microscope model, operator name, etc.
Resolution	Pixels per meter. Image device like microscopes have high resolution value;
Clear All	Click the Clear All button will clear the calibrated Magnification ;
Delete	Click Delete to delete the selected Magnification ;
Up	Click Move Up to move up the selected Magnification ;
Down	Click Move Down to move the selected Magnification down;

7.4.3 Settings>Image Format




Figure 7-4 Comprehensive Image Format Settings Page

Image Format	JPEG: The extension of JPEG file can get very high compression rate and display very rich and vivid images by removing redundant images and color data. In other words, it can get better image quality with the least disk space. If Measurement Objects are available, the Measurement Objects will be burned into the image and the Measurement Objects cannot be edited. TIFF: Tag Image File Format(TIFF) is a flexible bitmap format that is mainly used to store images including photos and artistic images.
Measurement Object Saving Method	Burn in Mode: The Measurement Objects are merged into the current image. User could not edit the Measurement Objects anymore. This mode is not reversible. Layered Mode: The Measurement Objects are saved in different layer with current image data in the target file. User could edit the Measurement Objects in the target file with some software on the PC. This mode is reversible.

7.4.4 Settings>Video




Figure 7-5 Comprehensive Setting of Video Settings Page-Playback




Figure 7-6 Comprehensive Setting of Video Settings Page-Video Encode

Fast Forward/Reverse Interval	The time interval of the playback of video files.
Video Encode	User can choose H264 or H265 encoding. H265 encoding can significantly reduce encoding bandwidth and save storage space under the same encoding quality;

7.4.5 Setting>Storage




Figure 7-7

Figure 7-8 Comprehensive Setting of SD Card Setting Page

Storage	SD Card: SD Card is only supported as the storage device.
File System Format of the Storage Device	List the file system format of the current storage device FAT32: The file system of SD Card is FAT32. The maximum video file size of single file is 4G Bytes; exFAT: The file system of SD Card is exFAT. The maximum video file size of single file is 16E Bytes; NTFS: The file system of SD Card is NTFS. The maximum video file size of single file is 2T Bytes. Use PC to format the SD Card and switch between FAT32, exFAT and NTFS. Unknown Status: SD Card not detected or the file system is not identified;

7.4.6 Setting>Files




Figure 7-9 Comprehensive Setting of Files Settings Page

Image File Name	Auto: The image files will be saved automatically with the specified prefix. Manual: Users has to specify the file name before image saving.
Video File Name	Auto: The video file will be saved automatically with the specified prefix. Manual: Users has to specify the Video File Name before video recording.

7.4.7 Setting>Time




Figure 7-10 Time Setting

Time	User can set Year , Month , Day , Hour , Minute and Second ital. in this page.
-------------	--

7.4.8 Setting>Language




Figure 7-11 Comprehensive Setting of Language Selection Setting Page

English	Set language of the whole software into English ;
Simplified Chinese	Set language of the whole software into Simplified Chinese ;
Traditional Chinese	Set language of the whole software into Traditional Chinese ;
Korean	Set language of the whole software into Korean ;
Thailand	Set language of the whole software into Thailand ;
French	Set language of the whole software into French ;
German	Set language of the whole software into German ;
Japanese	Set language of the whole software into Japanese ;
Italian	Set language of the whole software into Italian ;
Russian	Set language of the whole software into Russian ;

7.4.9 Comprehensive Miscellaneous Settings Page




Figure 7-12 Comprehensive Miscellaneous Settings Page

Ruler	Select to display the Ruler in the video window, or not to display the Ruler ;
Measurement	Select to display the Measurement toolbar in the video window, otherwise, the Measurement toolbar will not be displayed;
Overlay	Select to support saving graphics Overlay information in fusion mode, and not to save graphics Overlay information in fusion mode;
Auto Exposure	The maximum exposure time during auto exposure process could be specified. Setting this item to a lower value could guarantee a faster frame rate during Auto Exposure ;
ROI Color	Choosing the ROI rectangle line color ;
Camera Parameters Import	Import the Camera Parameters from the SD card to use the previously exported Camera Parameters ;
Camera Parameters Export	Export the Camera Parameters to the SD card to use the previously exported Camera Parameters ;
Reset to factory defaults	Restore camera parameters to its factory status;

8 Sample Photos Captured with XCAM1080P Series Camera




Figure 8-1 Suber Cell Captured with XCAM1080P2MPA




Figure 8-2 Monocot Stem Captured with XCAM1080P2MPA

9 Contacting Customer Service

Please contact your local distributor if you have any questions about the product.